

Návod k nastavení Siemens Gigaset C590 IP

1) Přihlaste se do Vašeho webového rozhraní a postupujte dle jednotlivých kroků.

ha-vel®

Welcome
You can use this interface to administer your device. For your security, the configuration program is protected with the system PIN.
Please choose your language for menus and dialogs: English
Please enter your system PIN:
Defaultní PIN : 0000

→ Settings Changing the Settings, you can fully adapt all features and functions of your device to your needs. You can configure new VoIP accounts and save your settings. It is recommended to consult the user's manual and the help function for detailed information on each setting.	
→ Status In the Status section, you can review important information about your device and your network.	

Home	Settings	Status		Log Off
Network	Add	Iress Assignment		?
IP Configuration		IP address type:	Obtained automatically	
Security Telephony		IP Address:		
Messaging		Subnet mask:		
Info Services Directories		Default Gateway:		
Management	Pre	ferred DNS server:		
	Alte	ernate DNS server:		
			Show Advanced Settings	
			Set Cancel	

ha-vel®

Home	Settin	igs	Status						Log Off
Network		Overvie	ew of connections						?
Telephony				Name	Provider	Status	Active		
Connections									
Audio				Fixed Line		Disconnected		Edit	
Number Assignmer	ıt				Gigaset		_		
Call Divert				Gigaset.net	Communications	Disabled		Edit	
Dialling Plans			1	IP1	Other Provider	Not configured		Edit	
Network Mailboxes									
Advanced VoIP settin	ngs		2.					Edit	
Messaging			2					Edit	
Info Services			э.					Lun	
Directories			4.					Edit	
Management								F-1 2	
			5.					Edit	
			6.					Edit	
		Provi	der or PBX profile						
				A profile conta	ins all relevant settings	for your provider	or phone	e system (PBX).	
		Automat	ic check for profile updates:	• Yes 🔘	No				
			Lpudico.		ndata Drafila				
				0	puate Prome				
				Cot	Concel				
				Set	Calicel				

Home	Settin	ngs	Status	Log	Off
Network			4. IP Connection		?
Telephony				Assign a connection name or actual phone number for	
Connections				identification.	
Audio Number Assignmen	nt	Co	nnection Name or Number:	IP1	
Call Divert		VoIP Con	figuration / Profile Download		
Dialling Plans Network Mailboxes				Start Configuration Assistant	
Advanced VoIP settin Messaging	ngs		Provider:	Other Provider	
Info Services			Profile Version		
Directories		Perso	onal Provider Data		
Management		Aut	thentication name:		
		Authen	tication password:		
			Username:		
			Display name:		
Zde vybere	me rozš	ířené n	astavení	Show Advanced Settings	
				Set Cancel Delete Connection	
L	_		_		



Vybereme rozšířené nastavení a nastavíme parametry účtu a uložíme.

a) pro ha-loo:
 username= 9 místné ha-loo číslo
 heslo= heslo k ha-loo
 proxy server= ustredna.ha-vel.cz

b) pro ha-loo Centrála:
 username= 10 místné číslo klapky
 heslo= heslo k dané klapce
 proxy server= sip server uvedeny u dané klapky na webu (pbx1.ha-loo.cz)

c) pro ha-loo mobil:
username= hmo cislo
heslo= heslo k SIP
proxy server= pbxm.ha-loo.cz
Proxy server port= 5665

Obrázek nastavení naleznete na další straně.



Home	Settings	Status		Log Off
Network Telephony		4. IP Connection	Assign a connection name or actual phone number for	?
Connections Audio Number Assignment		Connection Name or Number:	ha-loo	
Call Divert Dialling Plans Network Mailboxes	Vo	IP Configuration / Profile Download	Start Configuration Assistant	
Advanced VoIP setti	ngs	Provider:	Other Provider	
Info Services		Profile Version		
Directories	Perso	onal Provider Data		
Management	A	uthentication name:	username	
	Authe	ntication password:	heslo	
		Username:	username	
		Display name:	username	
			Hide Advanced Settings	
	Gen	eral data for your service provider		
		Domain:	ha-loo.cz	
	Pro	oxy server address:	proxy server	
		Proxy server port:	5060	
		Registration server:	proxy server	
	Regi	stration server port:	5060	
	Regis	tration refresh time:	600 sec	
	Netw	vork data for your service provider		
		STUN enabled:	O Yes 🖲 No	
	51	UN Server address:		
		STUN server port:	34/8	
		STUN refresh time:	240 sec	
		NAI retresh time:	20 sec	
		loouna proxy mode:	O Always O Automatic Never	
	Outbou	ind server address:		
	0	utbound proxy port:	5060	
	Sele	CLINETWORK PROTOCOL	UDP only	
			Set Cancel Delete Connection	

Potvrdíme tlačítkem "Set"

ha-vel®

Po uložení by měl být tento náhled. Pokud se Vám tento náhled nezobrazí, je třeba obnovit stránku.

Home	Settings	Status						Log Off
Network	Overvi	iew of connections						?
Telephony			Name	Provider	Status	Active		
Connections								
Audio			Fixed Line		Disconnected		Edit	
Number Assignmen	ıt			Ginaset				
Call Divert			Gigaset.net	Communications	Disabled		Edit	
Dialling Plans		1	ba-loo	Other Provider	Registered		Edit	
Network Mailboxes		i.	nanou	Other Flowider	Registered		Lun	
Advanced VoIP settin	ngs	2.					Edit	
Messaging								
Info Services		3.					Edit	
Directories		4					Edit	
Management								
		5.					Edit	
							T-dit	
		6.					Edit	
	Prov	vider or PBX profile						
			A profile contain:	s all relevant setting:	s for your provide	r or phone	e system (PBX).	
	Autom	atic check for profile						
	, acorn	updates:	Ves ON	0				
			Upd	late Profile				
			Sot	Cancol				
			Jet	Cancer				
								_

Pro manuální nastavení jednotlivých ruček využijte nastavení viz. obrázek níže.

Home	Settings	Status				Log Off
Network Telephony Connections		Handsets	Select the connection incoming calls for e	on for outgoing ca ach handset.	alls and also one or more connectio	ns for ?
Audio Number Assignmen Call Divert Dialling Plans Network Mailboxes Advanced VoIP setti Messaging Info Services	nt		Name Connection ha-loo Select line for each outgoing call	for outgoing calls ©	for incoming calls	
Management						